

Product Data Sheet

STARCOAT PMMA TPO PRIMER

Starcoat PMMA TPO Primer is a one-component primer used as a bonding agent between FPO and TPO sheets and Starcoat PMMA cold applied liquid waterproofing systems.

Material

1-component, solvent-free, polyurethane-based primer.

Properties and advantages

- Easy application.
- Low consumption rate.

Use

Starcoat PMMA TPO Primer is used as a bonding agent between FP and TPO sheets and Starcoat PMMA liquid waterproofing systems.

Packaging

0.8kg metal bottle

Colours

Starcoat PMMA TPO Primer is unpigmented.

Storage

Products should be stored sealed in their original airtight container and in a cool, dry, frost-free place. Unopened products have a shelf life of at least 6 months. Direct sunlight on the containers should be avoided, including on site. After removing some of the contents, reseal the containers so they are airtight.

Note: Once opened, the product has limited shelf life and may gel prematurely. Do not use any product that has gelled.

Application conditions

TEMPERATURES	The product can be applied within the following temperature ranges:		
Product	Temperature range in °C		
	Air	Substrate*	Material
Starcoat PMMA G Primer	+3 to +35	+3 to +50*	+3 to +30

*The substrate temperature must be at least 3°C above the dew point during application and curing.

Moisture

The relative humidity must be ≤90%.

The surface to be coated must be dry and ice-free. It must be protected from moisture until the coating has hardened.

Drying times

Temperature	Drying time for Starcoat PMMA G Primer
30°C	approx. 30 minutes
20°C	approx. 30 minutes
10°C	approx. 60 minutes
3°C	approx. 60 minutes

Consumption rates

0.03 – 0.05kg/m²

Technical Data

Density	0.91g/cm ³
---------	-----------------------

Product application

Application equipment/tools

For applying the product: Brush.
Roller.

Substrate preparation

Clean the substrate with Starcoat PMMA Cleaner and a lint-free cloth and allow the surface to dry completely (approx. 15 minutes) prior to application of the product.

Mixing

Mix the primer thoroughly by stirring or shaking before application.

Application

Brush apply a thin coat of primer to the substrate.

Avoid a build-up of excess material in all areas particularly in corners. If required, use the brush to spread the product more evenly and avoid greater layer thicknesses.

Note: If too little product is applied, curing problems may arise due to interrupted polymerisation.

Cleaning

If work is interrupted or when it is completed, clean the tools thoroughly with Starcoat PMMA Cleaner within the pot life of the product (approx. 10 minutes). This can be done with a brush. Do not use the tools again until the Starcoat PMMA Cleaner has fully evaporated.

Safety and risks

Please refer to the Safety Data Sheet (SDS) for the products used.

General information

The above product and application information is based on extensive development work and experience and is provided to the best of our knowledge. However, the wide variety of requirements and conditions on site mean that it is necessary for the product to be tested to ensure that it is suitable for the intended purpose. Only the most recent version of the document is valid. We reserve the right to make changes to reflect advances in technology or improvements to our products. Axter Ltd makes no warranties, express or implied, as to the properties and performance under any variations from such conditions in actual construction.

Axter Ltd reserves the right to modify and update this data at any time without prior notice. Only the latest version of this document is valid, available for download at www.axter.co.uk/downloads. Once downloaded, documents are uncontrolled. Users should always confirm they are referring to the latest version prior to use. Further assistance is available from Axter Ltd's Technical Support Team, email: technical@axterltd.co.uk, telephone: 01473 935008.

The intended use of this product should be verified with Axter Ltd prior to adoption to ensure its suitability and compliance with specifications, project requirements, industry regulations, legislation, good practice, installation techniques and all other relevant guidance. Axter Ltd accepts no liability for non-compliant use of this product.